

# Yealink MB-FS-Lift Datasheet

MB-FS-Lift is compatible with Yealink display devices and has a practical storage tray. It supports electric height adjustment with a range of up to 500mm and features a height memory function, allowing users to switch between different heights easily.



## Key Features and Benefits

**Flexible Height Adjustment** The floorstand supports electric height adjustment and height memory functions, with a lifting range of up to 500mm, flexibly meeting the height requirements for writing and communication. **Integrated Power Supply Design** The column of the floorstand is equipped with a universal socket, allowing direct power supply to the conference display without the need for additional outlets or extension cords. **Efficient Mobility and Stability** The floorstand is equipped with large swivel casters, ensuring flexible movement across different environments and making it easy to quickly adjust the position of the equipment.

# Specifications

Parameter	Description
Physical Parameters	Floorstand dimensions (L/W/H): 1100 x 600 x (1100~1600)mm Floorstand packaging dimensions: 1210 x 705 x 225mm Floorstand gross weight: 40kg Floorstand net weight: 34kg Tray dimensions: 700 * 200mm Tray weight: 2.8kg
Basic Parameters	Standby Power Consumption (plugged in, 85kg load, no lifting): 22 W Operating Power Consumption (plugged in, 85kg load, lifting): 880~990 W No-load Power Consumption (plugged in, no load, lifting): 220~330 W Lifting Speed: 15mm/s Lifting height: 500mm Lifting Panel Functions: - Show lifting height - Height adjustment - Initialization - Light effect switch - Memory button - Setting button - Child lock
VESA Hole Patterns	400 x 400mm - 1000 x 600mm
Maximum Weight Capacity	Maximum weight capacity of floorstand: 87kg Maximum weight capacity of tray: 10kg
Physical Interfaces	1 AC power input interface 1 AC power output interface
Power Input	100-240V 5A
Power Output	100-240V 5A
Operating Temperature	0-40°C
Operating Humidity	20%-90%
Storage temperature:	-30-70°C

# Device Compatibility

For more information about mounts compatibility lists, refer to [Mounts Compatibility Lists](#).