

## AS20

SAT line amplifier

- It allows the passage of remote feeding.
- It works on frequencies between 900 and 2150.
- Gain with tilt to compensate the typical loss of coaxial cables.
- Die-cast Aluminium mechanics and female F-type connectors.



CODE		284013
Band	Hz	950 - 2150
Gain	dB	12-17
Noise figure	dB	8
Voltage	V	13 - 18
Consumption	mA	40@13V
Impedance	$\Omega$	75
Connector		F Femmina
Output level	dB $\mu$ V	105
Quantity	pcs	1
Dimensions	mm	1 x 1.5 x 70