

NLS-FR20 Series

Fixed Mount Barcode Scanner



Designed primarily for such applications as electronic tickets/coupons, mobile marketing and office automation, the NLS-FR20 series fixed mount barcode scanner is able to read barcodes from paper and mobile phones.

Features

■ Digital Barcode Data Capture

Capable of reading 1D and 2D barcodes off mobile phones.

■ Printed Barcode Data Capture

Capable of reading 1D and 2D barcodes printed on paper.

■ Swift Scanning

Delivers effortless, snappy and accurate reading of barcodes on various mobile phone LCD screens with different contrast ratios, colors and reflectance.

■ Easy to Use

Simple configuration by scanning the programming barcodes provided in the user guide.



NLS-FR20 Series

Fixed Mount Barcode Scanner

Specifications

Performance		
Processor	IOTC 0370 CHIP	
Image Sensor	640× 480 CMOS	
Interface	RS-232 (9.6~115.2Kbps) / USB 1.1 (HID-KBW, HID-POS)	
Symbologies	2D	PDF417, Data Matrix, QR Code
	1D	EAN-13, EAN-8, UPC-A, UPC-E, ISSN, ISBN, Codabar, Code 128, Code 93, ITF-6, ITF-14, Interleaved 2 of 5, Industrial 2 of 5, Standard 2 of 5, Matrix 2 of 5, GS1 Databar (RSS-Expand, RSS-Limited, RSS-14), Code 39, Code 11, MSI-Plessey, Plessey
Scan Mode	Sense mode, Continuous mode	
Resolution	10mil	
Light Source	White LED	
Scan Window	52mm× 69mm	
PCS	≥30%	
FOV	Diagonal: 68°, Horizontal: 42°, Vertical: 54°	
Mechanical/Electrical		
Power Consumption	1W (max.)	
Notification	Beep, LED indicator	
Dimensions (L x W x H)	127.3× 111.5× 94mm	
Weight	300g	
Environmental		
Operating Temperature	-10°C - +50°C	
Storage Temperature	-20°C - +60°C	
Humidity	5% - 95% (non-condensing)	
Ambient Light	0 ~ 100,000 LUX	
Certifications		
FCC Part15 Class B, CE EMC Class B		
Accessories		
Cable	RS-232 Cable	Equipped with a power connector; used to connect the scanner to a host device.
	USB Cable	Used to connect the scanner to a host device.
Power Adapter		Used to provide power for the scanner.
		Output: DC5V, 0.5A; Input: AC100~240V, 50~60Hz.

Specifications are subject to change without notice.

