



ANT1200A

FM band aerial complete with F connector. Different design for the **radio signals reception**.

CODE		213001
Elements	no.	1
Band		FM
Bandwidth	MHz	87.5-108
Gain	dBi	2.1
Front/Back ratio	dB	Omni
Return loss	dB	-16
Beamwidth (-3dB)	°	360
Wind load at 120km/h (720N/m ²)	kg (N)	3 (29.43)
Connector	Type	F
Impedance	Ω	75
Max mast (Ø)	mm	60
Dimensions (L x H)	cm	96 x 77
Quantity Masterbox	pcs	10
Unit weight	kg	0.90
Total weight	kg	10.6
Accessories		
Horizontal polarization		Included

Horizontal polarization Tilt adjustment
Auxiliary boom

N.P.
N.P.

