

อุปกรณ์ส่งสัญญาณเสียงและแสงในตัวเดียวกัน รุ่น AH-03127-BS ยี่ห้อ CEMEN
AH-03127-BS ELECTRONIC SOUNDER AND BEACON

- สามารถปรับความดังและปรับเสียงได้ 32 เสียง ความดังสูงสุด 114 dB ที่ 1 เมตร ใช้ไฟ 24 VDC

Electronic Sounder and Beacon

General

This electronic sounder is designed for use with fire alarm systems, security systems and industrial signaling systems. Combined sounder and beacon provides an audio-visual warning which is suitable for places where high sound output and visual indication is required.

Characteristics

- 32 signal tones selectable by Dip switch.
- High sound output with low current consumption.
- High efficiency lens for maximum light output.
- Volume Control as standard.
- Two sets of IN and OUT terminals, easy for installation.



AH-03127-BS



AH-03127-S

Specifications

Model	AH-03127-S	AH-03127-BS
Voltage	24V DC	
Current Consumption 24V DC (MAX)	35mA	40mA
Sound Output 24V DC dB (A) at 1 meter	Max. 114	
Volume Control	0 to -20dB adjustment	
Ingress Protection	IP44	
Ambient Temperature	-25°C ~ +80°C	
Material	Fire-proof plastic	
Dimensions	92.5mm(Dia.) x 94mm(H)	92.5mm(Dia.) x 110mm(H)
Weight	254g	278g

Order information

AH-03127-S	Electronic Sounder
AH-03127-BS	Electronic Sounder and Beacon