



Satellite Splitter 8 Way 2.4 GHz

Specification

Spec.	Frequency	MODEL
		CA 088/FA
Power Pass		All Port Power Pass
Insertion Loss	5-400 MHz	12.5 dB
	400-1000 MHz	13.5 dB
	1000-1750 MHz	14.0 dB
	1750-2400 MHz	15.0 dB
Return Loss (In)	5-400 MHz	8.0 dB
	400-1000 MHz	11.0 dB
	1000-1750 MHz	10.0 dB
	1750-2400 MHz	9.0 dB
Return Loss (Out)	5-400 MHz	8.0 dB
	400-1000 MHz	12.0 dB
	1000-1750 MHz	10.0 dB
	1750-2400 MHz	8.0 dB
Isolation Loss	5-400 MHz	11.0 dB
	400-1000 MHz	17.0 dB
	1000-1750 MHz	16.0 dB
	1750-2400 MHz	14.0 dB