# UROVO®

## Smart Infrared Thermometer

# H1200

—

H1200 is a stylish contactless infrared thermometer.

| | | | |
|---|---|---|---|
| Contactless measurement. | | Over temperature setting and notification. | |
| High accuracy MEMS Infrared. | | Built in buzzer. | |
| Dual color backlight. | | Fahrenheit and Celsius mode. | |
| Lightweight and ergonomic design. | | Automatic idle shut off. | |

# H1200 Specification

## Temperature Spec

| | |
|---|---|
| Measurement accuracy | ±0.2$^\circ$ C |
| Measurement time | ≦ 0.5s |
| Measurement distance | 3.0 - 5.0cm |
| Measurement range | 35.0$^\circ$ C - 42.9$^\circ$ C |
| Power | ≦ 50mw |
| Resolution | 0.1$^\circ$ C |

## Working Environment

| | |
|---|---|
| Temperature | 10$^\circ$ C - 40$^\circ$ C |
| Humidity | ≦ 85% |
| Rated voltage | DC 3.0 V (2 x AA batteries) |

## Basic Spec

| | |
|---|---|
| Storage temperature | -20$^\circ$ C-+50$^\circ$ C , <80%RH |
| Timed shutdown | 15s |
| Weight | 136.5 g |
| Dimension | 153*104*39mm |